

# FUSERBLOC

## 20 to 1250 A

- Functions
- Illustrations
- References BS88
- References NFC and DIN
- ▶ **Accessories**
- Enclosed fuse switches
- Characteristics
- Dimensions

### Accessories

#### NFC and DIN fuse blown indication



##### Use

For fuse cartridge with striker (size 14 x 51 ; 22 x 58 ; 0 ; 1, 2, 3 and 4).

##### Electrical principle

A NO/NC auxiliary contacts detects that the fuse has blown.

##### Connection to the control circuit

By fast-on terminal 6.35 mm.

##### Electrical characteristics

30000 operations.

##### References

###### NO/NC type auxiliary contacts for 2 pole

Rating (A)	Frame size	Fuse size	Contact(s)	References
50	11	14 x 51	1 <sup>st</sup>	3994 <b>0405</b>
100 ... 125	13	22 x 58	1 <sup>st</sup>	3994 <b>0210</b>
160	14	0	1 <sup>st</sup>	3994 <b>0216</b>
250 ... 400	15 / 16	1-2	1 <sup>st</sup>	3994 <b>0225</b>
630	17	3	1 <sup>st</sup>	3894 <b>1206</b>
800 ... 1250	18	4	1 <sup>st</sup>	3894 <b>1212</b>

###### NO/NC type auxiliary contacts for 3 pole

Rating (A)	Frame size	Fuse size	Contact(s)	References
32	0	14 x 51	1 <sup>st</sup>	3994 <b>0303</b>
50	11	14 x 51	1 <sup>st</sup>	3994 <b>0405</b>
100 ... 125	13	22 x 58	1 <sup>st</sup>	3994 <b>0310</b>
160	14	0	1 <sup>st</sup>	3994 <b>0316</b>
250 ... 400	15 / 16	1-2	1 <sup>st</sup>	3994 <b>0325</b>
630	17	3	1 <sup>st</sup>	3894 <b>1306</b>
800 ... 1250	18	4	1 <sup>st</sup>	3894 <b>1312</b>
50 ... 1250	11 ... 18		2 <sup>nd</sup>	3994 <b>1901</b>

###### NO/NC type auxiliary contacts for 3 pole or 3 pole + neutral

Rating (A)	Frame size	Fuse size	Contact(s)	References
50	11	14 x 51	1 <sup>st</sup>	3994 <b>0405</b>
100 ... 125	13	22 x 58	1 <sup>st</sup>	3994 <b>0410</b>
160	14	0	1 <sup>st</sup>	3994 <b>0416</b>
250 ... 400	15 / 16	1-2	1 <sup>st</sup>	3994 <b>0425</b>
630	17	3	1 <sup>st</sup>	3894 <b>1406</b>
800 ... 1250	18	4	1 <sup>st</sup>	3894 <b>1412</b>
50 ... 1250	11 ... 18		2 <sup>nd</sup>	3994 <b>1901</b>

##### Characteristics

Rating (A)	Contact type	Nominal current (A)	Operating current I <sub>o</sub> (A)			
			AC-13 250 VAC	AC-13 400 VAC	DC-13 24 VDC	DC-13 48 VDC
32 ... 1250	NO/NC	16	4	3	12	2