

General Description

The HXYG100N08NF use advanced SGT MOSFET

technology to provide low RDS(ON), low gate charge,

fast switching and excellent avalanche characteristics.

This device is specially designed to get better ruggedness and suitable.

General Features

V_{DS} =85V I_D =100A


 $R_{DS(ON)} < 5.6 m\Omega @ V_{GS} = 10V$

Applications


Consumer electronic power supply Motor control

Synchronous-rectification Isolated DC

Synchronous-rectification applications



DFN5X6-8L



N-Channel MOSFET

Package Marking and Ordering Information

Product ID	Pack	Marking	Qty(PCS)
HXYG100N08NF	DFN5X6-8L		5000

Absolute Maximum Ratings (T_c=25 °C unless otherwise noted)

Symbol	Parameter	Rating	Units
V _D s	Drain-Source Voltage	85	V
Vgs	Gate-Source Voltage	±20	V
I _D @T _C =25°C	Continuous Drain Current, V _{GS} @ 10V	100	А
I _D @T _C =100°C	Continuous Drain Current, V _{GS} @ 10V	63.3	А
Ірм	Pulsed Drain Current ²	400	А
EAS	Single Pulse Avalanche Energy ³	273.8	mJ
P _D @T _C =25°C	Total Power Dissipation ⁴	107.8	W
Тѕтс	Storage Temperature Range	-55 to 150	°C
TJ	Operating Junction Temperature Range	-55 to 150	°C
R_{θ} JC	Thermal Resistance from Junction-to-Ambient ³	1.16	°C/W
Reja	Thermal Resistance Junction-Ambient ¹	60	°C/W



N-SGT Enhancement Mode MOSFET

Electrical Characteristics (T_J = 25°C, unless otherwise noted)

Parameter		Symbol	Test Conditions	Min.	Тур.	Max.	Unit	
Static Characteristics								
Drain-Source Breakdown Voltage		V _{(BR)DSS}	V _{GS} = 0V, I _D = 250μA	85	-	-	V	
Gate-body Leakage current		Igss	V _{DS} = 0V, V _{GS} = ±20V	-	-	±100	nA	
Zero Gate Voltage Drain	T _J =25°C		V _{DS} = 85V, V _{GS} = 0V	-	-	1	μА	
Current	TJ=100℃	I _{DSS}		-	-	100		
Gate-Threshold Voltage	Gate-Threshold Voltage		V _{DS} = V _{GS} , I _D = 250μA	2	3	4	V	
Drain-Source on-Resistance	₂ 4	R _{DS(on)}	V _{GS} = 10V, I _D = 20A	-	4.3	5.6	mΩ	
Forward Transconductance ⁴		G fs	V _{DS} = 5V, I _D =20A	-	57.8	-	S	
Dynamic Characteristic	s ⁵		,	•				
Input Capacitance	Input Capacitance			-	4645	-	pF	
Output Capacitance		Coss	V _{DS} = 40V, V _{GS} =0V, f =1MHz	-	673	-		
Reverse Transfer Capacitance		C _{rss}		-	41	-		
Gate Resistance		Rg	f=1MHz	-	2.0	-	Ω	
Switching Characteristi	cs ⁵				I.			
Total Gate Charge		Qg		-	61.3	-	nC	
Gate-Source Charge		Qgs	V _{GS} = 10V, V _{DS} = 40V, I _D = 20A	-	21	-		
Gate-Drain Charge		Q _{gd}		-	11	-		
Turn-on Delay Time		t _{d(on)}		-	16.5	-	. ns	
Rise Time		tr	$V_{GS} = 10V, V_{DD} = 40V,$ $R_{G} = 3\Omega, I_{D} = 20A$	-	51.8	-		
Turn-off Delay Time		t _{d(off)}		-	37.1	-		
Fall Time		t _f		-	8.2	-		
Body Diode Reverse Recovery Time		t _{rr}		-	69	-	ns	
Body Diode Reverse Recovery Charge		Qrr	- I _F =20A, di/dt = 100A/μS	-	141	-	nC	
Drain-Source Body Diode Characteristics								
Diode Forward Voltage ⁴		V _{SD}	I _S = 20A, V _{GS} = 0V	-	-	1.2	V	
Continuous Source Current	T _C =25℃	Is	-	-	-	100	Α	

Notes:

- 1. Repetitive rating, pulse width limited by junction temperature $TJ(MAX)=150^{\circ}C$
- 2. The EAS data shows Max. rating . The test condition is V_{DD} =50V, V_{GS} =10V, L=0.4mH, I_{AS} =37A
- 3. The data tested by surface mounted on a 1 inch2 FR-4 board with 2OZ copper, The value in any given application depends on the user's specific board design.
- 4. The data tested by pulsed , pulse width ≤ 300us , duty cycle ≤ 2%.
- 5. This value is guaranteed by design hence it is not included in the production test.



Typical Characteristics




Figure 1. Output Characteristics




Figure 3. Forward Characteristics of Reverse




Figure 5. $R_{\rm DS(ON)}$ vs. $I_{\rm D}$




Figure 2. Transfer Characteristics




Figure 4. $R_{\text{DS}(\text{ON})}\,$ vs. $V_{\text{GS}}\,$





Figure 6. Normalized $R_{\text{DS(on)}}$ vs. Temperature







Figure 7. Capacitance Characteristics








Figure 9. Power Dissipation

Figure 10. Safe Operating Area






Figure 11. Normalized Maximum Transient Thermal Impedance





1) E_{AS} Test Circuits







2) Gate Charge Test Circuit






3) Switch Time Test Circuit





DFN5X6-8L Package Information



SYMBOL	MM			INCH		
	MIN	NOM	MAX	MIN	NOM	MAX
А	4.95	5	5.05	0.195	0.197	0.199
A1	4.82	4.9	4.98	0.190	0.193	0.196
D	5.98	6	6.02	0.235	0.236	0.237
D1	5.67	5.75	5.83	0.223	0.226	0.230
В	0.9	0.95	1	0.035	0.037	0.039
B1	0.254REF		0.010REF			
С	3.95	4	4.05	0.156	0.157	0.159
C1	0.35	0.4	0.45	0.014	0.016	0.018
C2		1.27TYP			0.5TYP	
θ1	8°	10°	12°	8°	10°	12°
L1	0.63	0.64	0.65	0.025	0.025	0.026
L2	1.2	1.3	1.4	0.047	0.051	0.055
L3	3.415	3.42	3.425	0.134	0.135	0.135
Н	0.24	0.25	0.26	0.009	0.010	0.010

Attention

- Any and all HUA XUAN YANG ELECTRONICS products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your HUA XUAN YANG ELECTRONICS representative nearest you before using any HUA XUAN YANG ELECTRONICS products described or contained herein in such applications.
- HUA XUAN YANG ELECTRONICS assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein.
- Specifications of any and all HUA XUAN YANG ELECTRONICS products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- HUA XUAN YANG ELECTRONICS CO.,LTD. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all HUA XUAN YANG ELECTRONICS products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of HUA XUAN YANG ELECTRONICS CO.,LTD.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production.

 HUA XUAN YANG ELECTRONICS believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc.

 When designing equipment, refer to the "Delivery Specification" for the HUA XUAN YANG ELECTRONICS product that you intend to use.