



Specification Control Drawing

Raychem

ZHCP







THE LEGS HAVE A TENDENCY TO POINT INWARDS. WHEN THE BASE IS PRESSED FLAT THE DEGREE OF INWARDS TURN ALLOWABLE IS AS FOLLOWS: -

$$\text{Nr.1} \qquad p2 = P1 \stackrel{+0}{-2.4} \\
 \text{Nr.2} \qquad p2 = P1 \stackrel{+0}{-1.5} \\
 \text{Nr.3} \qquad p2 = P1 \stackrel{+0}{-1.2} \\
 \text{Nr.4} \qquad p2 = P1 \stackrel{+0}{-0.7} \\
 \text{Nr.6} \qquad p2 = P1 \stackrel{+0}{-0.7} \\$$

Dimensions (in millimetres).

Part No.	P & P1	R	WB (base)	WL (legs)	Weight (Nom) G/M	Recomended Bundle Dia. Min.
Nr.1	16.2-18.6	2.55-3.45	1.275-1.725	1.75-2.50	62.5	80
Nr.2	10.2-11.7	2.55-3.45	1.275-1.725	1.50-2.00	40	50
Nr.3	8.1-9.3	2.55-3.45	0.935-1.265	1.40-1.725	30	40
Nr.4	4.7-5.4	1.27-1.73	0.680-0.920	0.68-0.92	12	20
Nr.6	13.2-15.2	2.55-3.45	1.275-1.725	1.50-2.00	50	65

Copyright (!)

Approval

Design

The copyright in this drawing is the property of Tyco Electronics UK Ltd. The drawing is issued on the condition that it is not copied, reproduced or disclosed to a third party, either in whole or in part without the prior written consent of Tyco Electronics UK Ltd.

Drawn A.LILLEY. Checked

Issue

Date June 2006

Conforms to ISO Recommendations 3rd Angle Projection Not to Scale

MKTG. Q.A.

Raychem		Specification Control Drawing		Part Number	ZHCP	Issue 10
Iss.	Date	E.C.R. No.	Details of Change			
6 7 8 9 10	November 1986 July 1987 July 1990 April 1996 June 2006	4711 5114 5564 T449 CR06-HM-007	Add P2 din Wall chang	n to latest rquirements n to Nr4 & Nr6 ge & NR7 added neged on NR4 ved		

Tyco electronics UK Ltd.

Faraday Road,
Swindon, Wiltshire, SN3 5HH
England
Telephone: (01793) 528171 Fax: 572516

Cage Code K1010

Tyco electronics Corporation
300, Constitution Drive,
Menlo Park, CA 94025
USA
Telephone (650) 361-3860 Fax: (650) 361-5579

Cage Code Code 06090