FAIRCHILD

SEMICONDUCTOR

September 1986 Revised March 2000

DM74AS257 • DM74AS258 3-STATE Quad 1 of 2 Line Data Selector/Multiplexers

General Description

These data selectors/multiplexers contain inverters and drivers to supply full on-chip data selection to the four 3-STATE outputs that can interface directly with data lines of bus-organized systems. A 4-bit word selected from one of two sources is routed to the four outputs. The DM74AS257 presents true data whereas the DM74AS258 presents inverted data to minimize propagation delay time.

This 3-STATE output feature means that n-bit (paralleled) data selectors with up to 300 sources can be implemented for data buses. It also permits the use of standard TTL registers for data retention throughout the system.

Features

- Switching specifications at 50 pF
- \blacksquare Switching specifications guaranteed over full temperature and V_{CC} range
- Advanced oxide-isolated, ion-implanted Schottky TTL process
- Functionally and pin for pin compatible with Schottky, low power Schottky, and advanced low power Schottky TTL counterpart
- Improved AC performance over Schottky, low power Schottky, and advanced low power Schottky counterparts
- 3-STATE buffer-type output drive bus lines directly
- Expand any data input point
- Multiplex dual data buses
- General four functions of two variables (one variable is common)
- Source programmable counters

Ordering Code:

Order Number	Package Number	Package Description
DM74AS257M	M16A	16-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150 Narrow
DM74AS257N	N16E	16-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300 Wide
DM74AS258M	M16A	16-Lead Small Outline Integrated Circuit (SOIC), JEDEC MS-012, 0.150 Narrow
DM74AS258N	N16E	16-Lead Plastic Dual-In-Line Package (PDIP), JEDEC MS-001, 0.300 Wide

Devices also available in Tape and Reel. Specify by appending the suffix letter "X" to the ordering code.

Connection Diagram



Function Table

	OUTPUT Y				
	SELECT	А	в	AS257	AS258
CONTROL					
Н	Х	Х	Х	Z	Z
L	L	L	Х	L	н
L	L	Н	Х	н	L
L	н	Х	L	L	н
L	н	Х	Н	н	L
H = HIGH Level					

L = LOW Level X = Don't Care

Z = High Impedance (OFF)

www.fairchildsemi.com



www.fairchildsemi.com

Absolute Maximum Ratings(Note 1)

Supply Voltage, V _{CC}	7V
Input Voltage	7V
Voltage Applied to Disabled Output	5.5V
Operating Free Air Temperature Range	0°C to +70°C
Storage Temperature Range	$-65^{\circ}C$ to $+150^{\circ}C$
Typical θ _{JA}	
N Package	75.0°C/W

Note 1: The "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. The device should not be operated at these limits. The parametric values defined in the Electrical Characteristics tables are not guaranteed at the absolute maximum ratings. The "Recommended Operating Conditions" table will define the conditions for actual device operation.

DM74AS257 • DM74AS258

Recommended Operating Conditions

Symbol	Parameter	Min	Nom	Max	Units
V _{CC}	Supply Voltage	4.5	5	5.5	V
V _{IH}	HIGH Level Input Voltage	2			V
V _{IL}	LOW Level Input Voltage			0.8	V
I _{ОН}	HIGH Level Output Current			-15	mA
I _{OL}	LOW Level Output Current			48	mA
T _A	Free Air Operating Temperature	0		70	°C

Electrical Characteristics

over recommended operating free air temperature range. All typical values are measured at $V_{CC} = 5V$, $T_A = 25^{\circ}C$.

Symbol	Pa	arameter	Conditions		Min	Тур	Max	Units	
V _{IK}	Input Clam Voltage	p	$V_{CC} = 4.5V, I_{I} = -18 \text{ mA}$				-1.2	V	
V _{OH}	HIGH Leve	I	$V_{CC} = 4.5V$, $I_{OH} = Max$		2.4	3.2		V	
	Output Volt	age	$I_{OH} = -2 \text{ mA}, V_{CC} = 4.5 \text{V to } 5.5 \text{V}$		$V_{CC} - 2$			V	
V _{OL}	LOW Level Output Volt		$V_{CC} = 4.5V, I_{OL} = Max$			0.35	0.5	V	
l _l	Input Curre	nt @	$V_{CC} = 5.5 V, V_{IH} = 7 V$ A, B, \overline{G}				0.1		
	Max Input	/oltage		Select			0.2	mA	
I _{IH}	HIGH Leve	I	V _{CC} = 5.5V, V _{IH} = 2.7V A, B, G Select				20	μΑ	
	Input Curre	nt					40		
I _{IL}	LOW Level		V _{CC} = 5.5V, V _{IL} = 0.4V Select All Others				-1	mA	
	Input Curre	nt					-0.5		
I _O (Note 2)	Output Driv	e Current	V _{CC} = 5.5V, V _O = 2.25V		-30		-112	mA	
I _{OZH}	Off-State O	utput Current,	$V_{CC} = 5.5V$				-50	μΑ	
	HIGH Leve	I Voltage Applied	$V_0 = 2.7V$						
I _{OZL}	Off-State O	utput Current,	$V_{CC} = 5.5V$				-50	μA	
	LOW Level	Voltage Applied	$V_0 = 0.4V$			-50		μΑ	
I _{CCH}	Supply	DM74AS257		Outputs HIGH		12.9	19.7	mA	
	Current	DM74AS258				8.8	13.5	mA	
I _{CCL}	Supply	DM74AS257	$V_{CC} = 5.5V$	Outputs LOW		19	30.6	mA	
	Current	DM74AS258	Outputs Open			15.8	24.6	mA	
I _{CCZ}	Supply	DM74AS257		Outputs Disabled		19.7	31.9	mA	
	Current	DM74AS258	1			15.5	25.2	mA	

Note 2: The output conditions have been chosen to produce a current that closely approximates one half of the true short-circuit output current, I_{OS}.

	Parameter	From	То	Conditions	Min	Max	Unit
t _{PLH}	Propagation Delay Time, LOW-to-HIGH Level Output	Data	Any Y	$V_{CC} = 4.5V$ to 5.5V, $C_L = 50$ pF,	1	5.5	ns
t _{PHL}	Propagation Delay Time, HIGH-to-LOW Level Output			$R_L = 500\Omega$	1	6	ns
t _{PLH}	Propagation Delay Time, LOW-to-HIGH Level Output	Select	Any Y		2	11	ns
t _{PHL}	Propagation Delay Time, HIGH-to-LOW Level Output				2	10	ns
t _{PZH}	Output Enable Time to HIGH Level	OUTPUT Control	Any Y		2	7.5	ns
t _{PZL}	Output Enable Time to LOW Level				2	9.5	ns
t _{PHZ}	Output Disable Time, from HIGH Level	OUTPUT Control	Any Y		1.5	6.5	ns
t _{PLZ}	Output Disable Time, from LOW Level				2	7	ns
t _{PLH}	Propagation Delay Time,	Data	Any	$V_{CC} = 4.5V$ to 5.5V,	1	5	
Symbol	Parameter Parameter Propagation Delay Time	From	То	Conditions	Min	Max	Unit
FEIT	LOW-to-HIGH Level Output		Ŷ	$C_L = 50 \text{ pF},$	1	5	ns
t _{PHL}	Propagation Delay Time, HIGH-to-LOW Level Output			$R_L = 500\Omega$	1	4	ns
t _{PLH}	Propagation Delay Time, LOW-to-HIGH Level Output	Select	Any Y		2	9.5	ns
t _{PHL}	Propagation Delay Time, HIGH-to-LOW Level Output				2	10	ns
t _{PZH}	Output Enable Time to HIGH Level	OUTPUT Control	Any Y		2	8	ns
t _{PZL}	Output Enable Time to LOW Level				2	10	ns
t _{PHZ}	Output Disable Time, from HIGH Level	OUTPUT Control	Any Y		1.5	6	ns
t _{PLZ}	Output Disable Time, from LOW Level				2	6.5	ns

I

-



www.fairchildsemi.com



Fairchild Semiconductor

		snace	Product Folders and Applica
find products	Home >> Find products >>		
Products groups	DM74AS257		Related Links
Analog and Mixed	3-STATE Quad 1 of 2 Line Data Selectors/Multiplexers		Request samples
<u>Signal</u>	I		Dotted line
Discrete	Contents	Datasheet	How to order products
Interface	General description Features Product	Download this	Product Change Notices
Logic	status/pricing/packaging	datasheet	(PCNs)
<u>Microcontrollers</u>		PDF	Dotted line
Non-Volatile		РДГ	Support
<u>Memory</u>			Dotted line
Optoelectronics	General description	e-mail this datash	<u>Distributor and field sales</u>
Markets and		[E-	representatives
applications	These data selectors/multiplexers contain		Dotted line
New products	inverters and drivers to supply full on-chip data	This page	Quality and reliability
Product selection and	selection to the four 3-STATE outputs that can	Print version	Dotted line Design tools
parametric search	interface directly with data lines of bus-		Design tools
Cross-reference	organized systems. A 4-bit word selected from		
search	one of two sources is routed to the four		
	outputs. The DM74AS257 presents true data		
technical information	whereas the DM74AS258 presents inverted data to minimize propagation delay time.		
buy products			
technical support	This 3-STATE output feature means that n-bit		
	(paralleled) data selectors with up to 300		
my Fairchild	sources can be implemented for data buses. It also permits the use of standard TTL registers		
company	for data retention throughout the system.		

back to top

Features

- Switching specifications at 50 pF
- Switching specifications guaranteed over full temperature and V_{CC} range
- Advanced oxide-isolated, ion-implanted Schottky TTL process
- Functionally and pin for pin compatible with Schottky, low power Schottky, and advanced low power Schottky TTL counterpart
- Improved AC performance over Schottky, low power Schottky, and advanced low power Schottky counterparts

- 3-STATE buffer-type output drive bus lines directly
- Expand any data input point
- Multiplex dual data buses
- General four functions of two variables (one variable is common)
- Source programmable counters

back to top

Product status/pricing/packaging

Product	Product status	Pricing*	Package type	Leads	Package marking	Packing method
DM74AS257M	Full Production	\$0.79	SOIC	16	\$Y&Z&2&T DM74AS 257M	RAIL
DM74AS257N	Full Production	\$0.79	DIP	16	\$Y&Z&4&T&P DM74AS257N	RAIL
DM74AS257SJ	Full Production	\$0.99	SOP	16	\$Y&Z&2&T AS257SJ	RAIL
DM74AS257MX	Full Production	\$0.79	SOIC	16	\$Y&Z&2&T DM74AS 257M	TAPE REEL
DM74AS257SJX		\$0.99	SOP	16	\$Y&Z&2&T AS257SJ	TAPE REEL

* 1,000 piece Budgetary Pricing

back to top

<u>Home</u> | <u>Find products</u> | <u>Technical information</u> | <u>Buy products</u> | <u>Support</u> | <u>Company</u> | <u>Contact us</u> | <u>Site index</u> | <u>Privacy policy</u>

© Copyright 2002 Fairchild Semiconductor