XUK2APANM12R

photo-electric sensor - XUK - receiver - Sn 30m - 12..24VDC - M12





Main

Range of product	OsiSense XU
Series name	General purpose single mode
Electronic sensor type	Photo-electric sensor receiver
Sensor name	XUK
Sensor design	Compact 50 x 50
Detection system	Thru beam
Material	Plastic
Type of output signal	Discrete
Supply circuit type	DC
Wiring technique	3-wire
Discrete output type	PNP
Discrete output function	1 NO
Electrical connection	1 male connector M12, 4 pins
Product specific application	-
Emission	Infrared thru beam
[Sn] nominal sensing distance	30 m thru beam need a transmitter XUK2AKSNM12T

Complementary

Complementary	
Enclosure material	PBT
Lens material	PMMA
Maximum sensing distance	45 m thru beam
Output type	Solid state
Add on output	Without
Status LED	1 LED (yellow) for output state
[Us] rated supply voltage	1224 V DC with reverse polarity protection
Supply voltage limits	1036 V DC
Switching capacity in mA	<= 100 mA (overload and short-circuit protection)
Switching frequency	<= 250 Hz
Voltage drop	<= 1.5 V (closed state)
Current consumption	<= 35 mA (no-load)
Delay first up	< 15 ms
Delay response	< 2 ms
Delay recovery	< 2 ms
Setting-up	Without sensitivity adjustment
Depth	50 mm
Height	50 mm
Width	18 mm
Product weight	0.075 kg

Environment

Product certifications	CE CSA UL
Ambient air temperature for operation	-2555 °C
Ambient air temperature for storage	-4070 °C
Vibration resistance	7 gn, amplitude = +/- 1.5 mm (f = 1055 Hz) conforming to IEC 60068-2-6
Shock resistance	30 gn (duration = 11 ms) conforming to IEC 60068-2-27
IP degree of protection	IP65 double insulation conforming to IEC 60529

Offer Sustainability


Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 0841 - Schneider Electric declaration of conformity
REACh	Reference not containing SVHC above the threshold



Product data sheet Dimensions Drawings

XUK2APANM12R

Dimensions




Product data sheet Mounting and Clearance

XUK2APANM12R

Mounting and Clearance

Possible Orientation of Elbowed Connector




Product data sheet Connections and Schema

XUK2APANM12R


Wiring Schemes

M12 Connector



1: (+) 3: (-) 4: OUT/Output

PNP Outputs



Product data sheet Performance Curves

XUK2APANM12R

Detection Curves

